by periodically polling the infusion apparatus **2514**, or slave, for information. In the exemplary embodiment, only when the slave is polled, the slave may send signals to the control unit **2522** only when the slave is polled. However, in other embodiments, the slave may send signals before being polled. Signals sent by way of this system may include, but are not limited to, control, alarm, status, patient treatment profile, treatment logs, channel selection and negotiation, handshaking, encryption, and check-sum. In some embodiments, transmission through the SRR antenna **2508** may also be halted during certain infusion operations as an added precaution against electrical disruption of administration of insulin to the patient.

[0893] In the exemplary embodiment, the SRR antenna **2508** may be coupled to electrical source circuitry via one or more pins **2516** on a transmission line **2512**. In various other embodiments a transmission line may comprise a wire, pairs of wire, or other controlled impedance methods providing a channel by which the SRR antenna **2508** is able to resonate at a certain frequency. The transmission line **2512** may reside on the surface of the substrate base **2500** and may be composed of the same material as the SRR antenna **2508**, such as gold-plated copper. Additionally, a ground plane may be attached to the surface of the substrate base opposite the transmission line **2512**.

[0894] The electrical circuitry coupled to the SRR antenna **2508** may apply an RF signal to the end of the transmission line **2512** nearest the circuitry, creating an electromagnetic field throughout, and propagating from, the SRR antenna **2508**. The electrical circuitry coupled to the SRR antenna **2508** facilitates resonance at a predetermined frequency, such as 2.4 GHz. Preferably, transmission line **2512** and SRR antenna **2508** both have impedances of 50 Ohms to simplify circuit simulation and characterization. However, in other various embodiments, the transmission line and split ring resonator antenna may have other impendence values, or a different resonating frequency.

[0895] Referring to FIG. **129**, a signal processing component(s) **2518**, such as, a filter, amplifier, or switch, may be integrated into the transmission line **2512**, or at some point between the signal source connection pins **2516** and the SRR antenna **2508**. In the exemplary embodiment, the signal processing component **2518** is a band-pass filter to facilitate desired signal processing, such as, allowing only the exemplary frequency to be transmitted to the antenna, and rejecting frequencies outside that range. In the exemplary embodiment, a Combline band-pass filter **2518** may be included in the transmission line **2512** between the antenna and the signal source. However in other embodiments, any other signal processing device, for example, but not limited to, filters, amplifiers, or any other signal processing devices known in the art.

[0896] In various embodiments, a SRR antenna **2508** may be composed of metallic bodies capable of resonating on a flexible or rigid substrate. As shown in FIG. **128** and FIG. **3**, the exemplary embodiment incorporates a curved SRR antenna on a flexible Polyimide substrate **2520**. Polyimide may be the exemplary material because it tends to be more flexible than alternative substrates. This configuration may allow for simplified integration into circular-shaped devices (such as a wirelessly controlled medical infusion apparatus **2514**), devices with irregular-shaped external housing, or devices in which saving space is paramount.

[0897] In various embodiments, both control unit **2522** and base unit **2514** may incorporate a split SRR antenna **2508**. This configuration may prove beneficial where the control unit is meant to be handheld, in close proximity to human skin, or is likely to be in close proximity to a varying number of materials with varying dielectric constants.

[0898] In various other embodiments, a SRR antenna **2508** may be integrated into a human or animal limb replacement. As prosthetic limbs are becoming more sophisticated the electrical systems developed to control and simulate muscle movements require much more wiring and data transfer among subsystems. Wireless data transfer within a prosthetic limb may reduce weight through reduced physical wiring, conserve space, and allow greater freedom of movement. However, common antennas in such a system may be susceptible to dielectric loading. Similar to the previously mentioned benefits of integrating a SRR antenna **2508** into a wirelessly controlled medical infusion apparatus, a prosthetic limb, such as a robotic arm, may also come into contact with human skin or other dielectric materials and benefit from the reduction of electrical disturbances associated with such an antenna. In other various embodiments, the SRR antenna **2508** may be integrated into any device comprised of the electrical components capable of powering and transmitting/receiving data to an antenna and susceptible to electrical disturbances associated with proximity to dielectric materials.

[0899] In various embodiments, a SRR antenna **2508** may be integrated into a configuration of medical components in which one or more implantable medical devices, operating within the human body, communicate wirelessly to a handheld, body-mounted, or remote control unit. In certain embodiments, both body-mounted and in-body wireless devices may utilize a SRR antenna **2508** for wireless communication. Additionally, one or more of the components utilizing a SRR antenna **2508** may be completely surrounded by human skin, tissue or other dielectric material. By way of example, such a configuration may be used in conjunction with a heart monitoring/control system where stability and consistency of wireless data transmission are of fundamental concern.

[0900] In various other embodiments, a SRR antenna **2508** may be integrated into the embodiments of the infusion pump assembly. Configuration of medical components in which one or more electrical sensors positioned on, or attached to, the human body wirelessly communicate to a remote transceiving unit. By way of example, a plurality of electrodes positioned on the body may be coupled to a wireless unit employing a SRR antenna **2508** for wireless transmission to a remotely located electrocardiogram machine. By way of further example, a wireless temperature sensor in contact with human skin may employ SRR antenna **2508** for wireless communication to a controller unit for temperature regulation of the room in which the sensor resides.

[0901] While the principles of the invention have been described herein, it is to be understood by those skilled in the art that this description is made only by way of example and not as a limitation as to the scope of the invention. Other embodiments are contemplated within the scope of the present invention in addition to the exemplary embodiments shown and described herein. Modifications and substitutions by one of ordinary skill in the art are considered to be within the scope of the present invention.